

IX Series Video Door Streaming to Hikvision® DS-7600 Series NVR

The IX Series video door stations can be viewed by the Hikvision client using the ONVIF Profile S. By default, the IX Series video door stations have the second video stream turned on and set to stream using the H.264 protocol. When configuring, verify the door stations settings.

Hikvision® DS-7600 Series Setup

- 1 Open the Hikvision Management client and Log in.
- 2 Click **Configuration** from the menu bar on top.
- 3 Select **IP Camera** under **Camera Management** from the menu on the left.
- 4 Select the **Channel No.** to be used, click **Modify** button.

The screenshot shows the Hikvision DS-7608NI-E2/8P Configuration interface. The top navigation bar includes 'Live View', 'Playback', 'Log', and 'Configuration' (highlighted with a red circle 2). The left sidebar shows 'Configuration' with 'IP Camera' selected under 'Camera Management' (highlighted with a red circle 3). The main area displays the 'IP Camera' table with columns: Channel No., IP Camera Address, Channel No., Management Port, Status, Protocol, and Version. A red box highlights the 'Modify' button and the row for Channel No. D03 (highlighted with a red circle 4).

Channel No.	IP Camera Address	Channel No.	Management Port	Status	Protocol	Version
D01	192.168.1.13	1	10080	Online	ONVIF	2.00
D02	192.168.1.95	1	80	Online	AXIS	5.50.3
D03	192.168.254.13	1	8000	Offline(IP camera does not exist)	HIKVISION	
D04	192.168.254.15	1	8000	Offline(IP camera does not exist)	HIKVISION	
D05	192.168.254.16	1	8000	Offline(IP camera does not exist)	HIKVISION	
D06	192.168.254.17	1	8000	Offline(IP camera does not exist)	HIKVISION	
D07	192.168.254.18	1	8000	Offline(IP camera does not exist)	HIKVISION	
D08	192.168.254.19	1	8000	Offline(IP camera does not exist)	HIKVISION	

- 5 Enter the Aiphone door stations information:

- **IP Address:** xxx.xxx.x.xx
- **Protocol:** ONVIF
- **Management Port:** 10080
- **Channel No.:** 1
- **User Name:** aiphone (default)
- **Password.:** aiphone (default)
- **Adding Method:** Manual

- 6 Click **OK**.

The screenshot shows the Hikvision DS-7608NI-E2/8P Configuration interface. The top navigation bar includes 'Live View', 'Playback', 'Log', and 'Configuration' (highlighted with a red circle 2). The left sidebar shows 'Configuration' with 'IP Camera' selected under 'Camera Management' (highlighted with a red circle 3). The main area displays the 'IP Camera' configuration form with fields: IP Camera Address (192.168.1.15), Protocol (ONVIF), Management Port (10080), Channel No. (1), User Name (aiphone), Password (masked), Confirm (masked), and Adding Method (Manual). A red box highlights the 'OK' button (highlighted with a red circle 6) and the 'User Name' field (highlighted with a red circle 5).

For more details about the features and information above, please contact Technical Support between 6:00am and 4:30pm (Pacific Time)