

IX Series Video Door Station Streaming to exacqVision® Client*

The IX Series video door stations can be viewed by the exacqVision client using the RTSP connection method. By default, IX Series video door stations have the second video stream turned on and set to stream using the H.264 protocol. When configuring, verify door station settings.

exacqVision® Client Screen Setup

Configuring with ONVIF instead of RTSP may cause errors. If ONVIF method was used, cycle power to the video door station and configure using the RTSP method described below.

- 1 Open the exacqVision client and click **Setup**  button.
- 2 Select **Add IP Cameras** from the menu on the left.
- 3 Click **New** button under IP Camera List.
- 4 Enter the door information into the **IP Camera Information** section.
 - **Device Type:** RTSP
 - **Hostname/IP Address:**
rtsp://[ip address]/udp/unicast/aiphone_H264
rtsp://[ip address]/udp/unicast/aiphone_JPEG
 - **Username:** aiphone
 - **Password:** aiphone
- 5 Click **Apply**.

Note:

When using the default H.264 protocol, enter the address ending in H264.
For MJPEG, use the Support Tool to change the streaming method of the video door station and enter address ending in JPEG.

The screenshot shows the 'exacqVision Client' window. On the left, the 'Configuration' tree has 'Add IP Cameras' selected. The main area is titled 'Add IP Cameras' and contains an 'IP Camera List' table with one entry: 'rtsp://192.168.0.13/udp/unicast/aiphone_H264' (RTSP, Connected). Below the table is a 'New' button. To the right is the 'IP Camera Information' form with fields for Device Type (RTSP), Hostname/IP Address (rtsp://192.168.0.13/udp/unicast/aiphone_H264), Port, Username (aiphone), Password (masked), and Password Confirm (masked). An 'Apply' button is at the bottom right of the form. At the bottom of the window, there is a 'Find IP Cameras' section with a search bar and a table of discovered cameras.

Enabled	Address	Type	Model	MAC	Firmware	Status
<input checked="" type="checkbox"/>	rtsp://192.168.0.13/udp/unicast/aiphone_H264	RTSP				Connected.

Add	Reported Name	Address	Type	Model	MAC	Firmware	Addressable	Systems
<input type="checkbox"/>	AXIS%20M1054	192.168.0.90	ONVIF	M1054			No	
<input type="checkbox"/>		192.168.0.206	ONVIF				No	
<input type="checkbox"/>		192.168.0.20	Panasonic	ST162	00-80-F0-44-91-1B		No	

* Tested with exacqVision® Client Version: 6.4.5.68890 (x86)