

SYSTEM/MODEL: AP-M

MODIFICATION: Using UL Listed power supplies

DIFFICULTY LEVEL: 4 - Moderate/hard - Internal connection or component addition.

COMPONENTS REQUIRED: 1. PS-1820UL power supply, 18V DC

- INSTR/OPERATIONS:**
1. Cut wires from large AC transformer to PC board (heavy red wires to points 27 and 28).
 2. Remove incoming AC power cord from master station.
 3. Reconnect the power on/off switch in series with the positive of power supply and pt. 27 on PC-381.
 4. Connect negative from the PS-1820UL power supply to GND terminal of master station.

See following schematic.

REFERENCE DRAWING #: 0698-016, 381-016

Aiphone's product warranty applies to products properly modified using these instructions.
However, if a unit is damaged as a result of improper modification, the warranty does not apply.

AP-M SYSTEM WITH UL LISTED POWER SUPPLIES

AP-10M Schematic Diagram

