

SYSTEM/MODEL: TD-H/B

MODIFICATION: Audio output to tape recorder

DIFFICULTY LEVEL: 4 - Moderate/hard - Internal connection or component addition.

COMPONENTS REQUIRED: Resistor: 10K ohm, 1/4 Watt.

Capacitor: 22mfd., 16V

- INSTR/OPERATIONS:**
1. Install resistor and capacitor in series off of + side of capacitor C12, and connect lead wire to positive side of recorder input.
 2. Connect ground lead to negative. See following schematic.

REFERENCE DRAWING #: 1298-1069, 1440-1069

Aiphone's product warranty applies to products properly modified using these instructions.
However, if a unit is damaged as a result of improper modification, the warranty does not apply.

